



Cisco Headset 500 Series

Contents

Product overview	3
Features and benefits	4
Platform support	8
Product specifications	18
Ordering information	19
Warranty information	21
Cisco environmental sustainability	21
Cisco Capital	22
For more information	22



The Cisco Headset 500 Series is a professional range of wired and wireless headsets optimized for Cisco IP phones, soft clients, and desktop video devices.

The 500 Series are headsets designed for workers in open work spaces to stay connected and productive in any environment. They feature vibrant audio, powerful noise isolation, exceptional comfort, and easy administration.

Product overview

The Cisco® Headset 500 Series delivers surprisingly vibrant sound for open workspaces. Users can stay focused in noisy environments with rich sound, exceptional comfort, and proven reliability. The 500 Series offers a lightweight form factor that is comfortable to wear, even for an entire workday. It's designed for workers who spend a lot of time wearing headsets for voice communications and listening to music.

The Headset 500 Series offers:

- Lightweight comfort that is ideal for extended wear
- Premium sound in a sleek form factor – great for music and voice communications
- Powerful noise isolation with unidirectional microphones that are designed to hone in on the user's voice and simultaneously minimize background noise
- Easy, intuitive user configuration experience when used with Cisco IP phones* and Cisco Jabber**
- Extended Digital Enhanced Cordless Telecommunications (DECT) range (300+ feet) with wireless models
- Flexible options for connecting to devices: various models support USB, RJ, 3.5 mm, DECT, and Bluetooth connections
- Proven reliability and integrations for Cisco IP phones, Cisco DX Series endpoints, and Cisco soft clients
- Easy device management including remote firmware upgrade, inventory management, diagnostics, and metrics when used with compatible Cisco Unified Communications Manager* and Webex Control Hub

* When using a compatible Cisco IP phone or Cisco Jabber version

Use the Cisco Headset 500 Series with the optional USB headset adapter for enhanced experiences, including with automatic software upgrades, in-call presence indicator, and audio customizations which allow you to adjust how you hear others and how they hear you.

Features and benefits

Table 1. Features and benefits for Cisco Headset 500 Series

Feature	Description
Integrated serviceability	Headsets are easier to deploy, manage, and service with Cisco collaboration plus headsets. Centrally manage policy, defaults, and much more when using Cisco Headsets with Cisco Unified Communications Manager, Cisco Webex Control Hub, and devices.
Premium audio and noise isolation	The microphone is exceptional at capturing wide bandwidth sound, with little signal noise and low distortion. It is composed of a high-quality electret capsule and unique housing design. The capsule's orientation in the microphone housing creates a short acoustic path, which provides maximum acoustic sensitivity (best voice reception) and balanced noise reduction. The optimized microphone capsule and housing create a clean and natural sound with reduced background noise so the user's voice can be clearly heard.
Lightweight and ergonomic design	Built with comfort in mind, these headsets are designed to be delightful to wear for extended periods of time and to reduce head fatigue. They feature quality materials, including multiaxial ear cups.
Advanced ear cup design	Our design creates a full and rich sound that makes collaboration easier and music more enjoyable. The ear cups feature efficient acoustic transducers and integrations.
Enhanced capabilities enabled by the USB headset adapter	Use this optional accessory to connect the headset to Cisco IP phones, Cisco DX endpoints, Cisco Jabber®, Cisco Webex Teams™ and Cisco UC-One. It offers a more enhanced experience with: <ul style="list-style-type: none"> • In-call indicators: LED(s) on the ear plate • Simplified call controls • Customized audio
Test and adjust microphone (record, playback, gain)**	The microphone test removes the guesswork associated with tuning microphone gain levels by enabling users to record themselves speaking in their work environment and then playing the recordings back.
Audio shaping**	This feature enables users to get the best phonic experience by shaping the inbound audio.

** Feature requires a USB interface for headsets and a compatible Cisco IP phone and firmware, or a compatible Jabber version.



Figure 1.
Cisco Headset 521 and 522 and in-line USB adapter

Table 2. Features and benefits of Cisco Headset 521 and 522

Feature	Description
Power 3.5-mm connector	Enables flexible headset use with standard 3.5-mm jacks on laptops, tablets, and mobile phones and connects headset LEDs to power when using an in-line USB headset adapter.
In-line USB adapter	The hand-held controller connects 3.5-mm headset to USB and provides easy access to key call control capabilities, including answer call, end call, reject call, hold/resume (for multiple calls), mute/unmute, volume up, and volume down.

Note: The Cisco Headset 521 and 522 terminate with a power 3.5-mm connector and include an in-line USB adapter.



Figure 2.
Cisco Headset 531, 532, and desktop USB headset adapter

Table 3. Features and benefits for Cisco Headset 531 and 532

Feature	Description
Quick disconnect cabling options	Easily plug and unplug the headset as needed during shift changes or breaks with high-cycle quick disconnect.
Desktop USB adapter option	Connects quick disconnect to USB and provides easy access to key call control capabilities, including answer call, end call, reject call, hold/resume (for multiple calls), mute/unmute, volume up, and volume down.
Quick disconnect RJ9 option	Provides the broadest range of Cisco IP phone connectivity.

Note: The Cisco Headset 531 and 532 terminate with quick disconnect and are bundled with either a desktop USB adapter or RJ9 cabling option.



Figure 3. Cisco Headset 561 and 562 with Standard Base Station

Table 4. Features and benefits for Cisco Headset 561 and 562 with Standard Base Station

Feature	Description
Enhanced mobility wireless	The newest in DECT technology provides freedom to roam up to 300+ feet from the base with crystal clear audio.
On-ear controls	Enjoy easy access to key call control capabilities, including answer call, end call, reject call, hold/resume (for multiple calls), mute/unmute, volume up, and volume down.
Full security	AES-128 encryption ensures secured communication.
Music mode	Full-band audio provides premium, 48-kHz audio experience.
Conference/Training Mode	Pair up to three additional headsets to the same base station for easy, comfortable training. Each headset will retain its own settings and will automatically be on mute when added.
Multi-mode audio	Automatically provides the best available audio experience in call mode (narrowband or wideband) and (wideband or full band) in music mode.

Feature	Description
Auto-answer	The headset automatically answers calls when undocked. The headset will automatically end calls when docked.
All cables included	The Standard base comes with a USB-A cable for USB connectivity and an RJ9/11 Y cable for Cisco IP phone connectivity, making it easier and less expensive to order Cisco headsets for use with Cisco devices. USB-C cables can be purchased separately for using the headset with USB-C compatible devices.



Figure 4.
Cisco Headset 561 and 562 with Multibase Station

Table 5. Features and benefits for Cisco Headset 561 and 562 with Multibase Station

Feature	Description
Standard features	All features listed in the Standard base station.
Multiple sources	Simultaneously connect to multiple physical and Bluetooth sources. Select a connection with the source selector buttons on the base station.
Auto-source selection	The headset can answer calls from any source with a single press of a button. The Multibase station will automatically select the source with the incoming call.
Bluetooth connectivity	Pair Bluetooth devices to the base for convenient connectivity to mobile devices and phones. The Multibase station supports four paired devices and one active Bluetooth connection.
All cables included	The Multibase station comes with two USB-A cables for USB connectivity and an RJ9/11 Y cable for Cisco IP phone connectivity, making it easier and less expensive to order Cisco headsets for use with Cisco devices. USB-C cables can be purchased separately for using the headset with USB-C compatible devices.

Platform support

Note: Table 6-7 lists support for basic call control and serviceability functionalities. Advanced call control support may be available only in the latest version of software. Legacy Cisco phones, third-party apps, and third-party devices may work with the Cisco Headset 500 Series, but they have limited or no testing coverage and are not officially supported by Cisco.

Basic call control support: Mute/Unmute/Volume+/Volume-/Answer Call/End Call.

Advanced call control support: Reject call/Hold call/Resume call/Multiple call handling.

Table 6. Call control support

Model	Headset 521 / 522		Headset 531 / 532		Headset 561 / 562		
	3.5 mm (Audio Only)	USB	RJ9 (Audio Only)	USB	RJ9/RJ11 (Y)	USB	BT
Cisco IP Phone 6821 MPP	N/A	N/A	Yes	N/A	N/A	N/A	N/A
Cisco IP DECT Phone 6825 MPP	Yes	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Phone 6841 MPP	N/A	N/A	Yes	N/A	N/A	N/A	N/A
Cisco IP Phone 6851 MPP	N/A	N/A	Yes	N/A	No	N/A	N/A
Cisco IP Phone 6861 MPP	N/A	N/A	Yes	N/A	No	N/A	N/A
Cisco IP Phone 6871 MPP	N/A	Yes: Phone load 11.3(1) or later Headset load 1.5(1) or later	Yes	Yes: Phone load 11.3(1) or later Headset load 1.5(1) or later	Yes: Phone load 11.3(1) or later Headset load 1.0(2) or later	Yes: Phone load 11.3(1) or later Headset load 1.0(2) or later	N/A
Cisco IP Phone 7811	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Phone 7821	N/A	N/A	Yes	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A	N/A
Cisco IP Phone 7841	N/A	N/A	Yes	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A	N/A

Model	Headset 521 / 522		Headset 531 / 532		Headset 561 / 562		
	3.5 mm (Audio Only)	USB	RJ9 (Audio Only)	USB	RJ9/RJ11 (Y)	USB	BT
Cisco IP Phone 7861	N/A	N/A	Yes	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A	N/A
Cisco IP Phone 7811 MPP	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Phone 7821 MPP	N/A	N/A	Yes	N/A	No	N/A	N/A
Cisco IP Phone 7841 MPP	N/A	N/A	Yes	N/A	No	N/A	N/A
Cisco IP Phone 7861 MPP	N/A	N/A	Yes	N/A	No	N/A	N/A
Cisco IP Conference Phone 7832	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Conference Phone 7832 MPP	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Phone 8811	N/A	N/A	Yes	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A	N/A
Cisco Wireless IP Phone 8821	Yes	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Phone 8841	N/A	N/A	Yes	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A	N/A
Cisco IP Phone 8845	N/A	N/A	Yes	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later

Model	Headset 521 / 522		Headset 531 / 532		Headset 561 / 562		
	3.5 mm (Audio Only)	USB	RJ9 (Audio Only)	USB	RJ9/RJ11 (Y)	USB	BT
Cisco IP Phone 8851	N/A	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later
Cisco IP Phone 8861	N/A	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes; Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later
Cisco IP Phone 8865	N/A	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later
Cisco IP Phone 8865NR	N/A	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 12.1(1) or later Headset Load 1.5(1) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	Yes: Phone load 12.5(1)SR2 or later Headset Load 1.0(2) or later	N/A
Cisco IP Phone 8811 MPP	N/A	N/A	Yes	N/A	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	N/A	N/A
Cisco IP Phone 8841 MPP	N/A	N/A	Yes	N/A	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	N/A	N/A

Model	Headset 521 / 522		Headset 531 / 532		Headset 561 / 562		
	3.5 mm (Audio Only)	USB	RJ9 (Audio Only)	USB	RJ9/RJ11 (Y)	USB	BT
Cisco IP Phone 8845 MPP	N/A	N/A	Yes	N/A	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	N/A	No
Cisco IP Phone 8851 MPP	N/A	Yes: Phone load 11.1(2) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 11.1(2) or later Headset Load 1.5(1) or later	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	No
Cisco IP Phone 8861 MPP	N/A	Yes: Phone load 11.1(2) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 11.1(2) or later Headset Load 1.5(1) or later	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	No
Cisco IP Phone 8865 MPP	N/A	Yes: Phone load 11.1(2) or later Headset Load 1.5(1) or later	Yes	Yes: Phone load 11.1(2) or later Headset Load 1.5(1) or later	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset Load 1.0(2) or later	No
Cisco IP Conference Phone 8832/8832NR	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Conference Phone 8832 MPP	N/A	N/A	N/A	N/A	N/A	N/A	N/A
Cisco IP Phone 6900/79x2/79x5/8900/9900 Series	N/A	No	Interoperability verified with those models with RJ9 headset port, but not officially supported by Cisco	No	Interoperability verified with those models with RJ9 headset port and RJ11 auxiliary port for basic call control, but not officially supported by Cisco (Please set sidetone to "off" to avoid echo.)	No	No

Model	Headset 521 / 522		Headset 531 / 532		Headset 561 / 562		
	3.5 mm (Audio Only)	USB	RJ9 (Audio Only)	USB	RJ9/RJ11 (Y)	USB	BT
Cisco SPA Series IP Phone	No	No	No	No	No	No	No
Cisco Jabber Client - Desktop	Yes	Yes: Jabber load 12.0 or later Headset load 1.5(1) or later	N/A	Yes: Jabber load 12.0 or later Headset load 1.5(1) or later	N/A	Yes: Jabber load 12.5 or later Headset load 1.0(2) or later	No
Cisco Jabber Client - Mobile	Yes	N/A	N/A	N/A	N/A	N/A	Audio Only
Cisco Jabber Client - VDI	Yes	Yes: Jabber load 12.0 or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later	N/A	Yes: Jabber load 12.0 or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later	N/A	Yes: Jabber load 12.5 or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later	No
Cisco Webex Teams - Desktop	Yes	Yes: Headset load 2.0(1) or later	N/A	Yes: Headset load 2.0(1) or later	N/A	Yes: Headset load 2.0(1) or later	No
Cisco Webex Desktop Series	N/A	Yes: Webex Desktop load 9.8 or later Headset load 1.5(1) or later	N/A	Yes: Webex Desktop load 9.8 or later Headset load 1.5(1) or later	N/A	Yes: Webex Desktop load 9.8 or later Headset load 1.5(1) or later	No
Cisco Webex Meetings	Yes	Mute/ Unmute Only	N/A	Mute/ Unmute Only	N/A	Mute/ Unmute Only	No

Model	Headset 521 / 522		Headset 531 / 532		Headset 561 / 562		
	3.5 mm (Audio Only)	USB	RJ9 (Audio Only)	USB	RJ9/RJ11 (Y)	USB	BT
Cisco UC-One	Yes	Yes: UC-One load 22.9 or later Headset load 1.5(1) or later	N/A	Yes: UC-One load 22.9 or later Headset load 1.5(1) or later	N/A	Yes: UC-One load 22.9 or later Headset load 1.5(1) or later	No
Microsoft Skype for Business	Yes	Interoperability verified, but not officially supported by Cisco Headset load 2.0 (1) or later	N/A	Interoperability verified, but not officially supported by Cisco Headset load 2.0 (1) or later	N/A	Known to work, but not officially supported by Cisco Headset load 2.0 (1) or later	No

Table 7. Serviceability support

Model	Local Config	Remote Firmware Upgrade / Management	Inventory Management	Diagnostics	Remote Config
Cisco IP Phone 6821 MPP	No	No	No	No	No
Cisco IP DECT Phone 6825 MPP	No	No	No	No	No
Cisco IP Phone 6841 MPP	No	No	No	No	No
Cisco IP Phone 6851 MPP	No	No	No	No	No
Cisco IP Phone 6861 MPP	No	No	No	No	No
Cisco IP Phone 6871 MPP	Yes: Phone load 11.3(1) or later Headset load 1.5(1) or later	Yes: Phone load 11.3(1) or later Headset load 1.5(1) or later	No	Yes: Phone load 11.3(1) or later Headset load 1.5(1) or later	No
Cisco IP Phone 7811	N/A	N/A	N/A	N/A	N/A

Model	Local Config	Remote Firmware Upgrade / Management	Inventory Management	Diagnostics	Remote Config
Cisco IP Phone 7821	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later
Cisco IP Phone 7841	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later
Cisco IP Phone 7861	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/11.5(1)SU7 or later
Cisco IP Phone 7811 MPP	No	No	No	No	No
Cisco IP Phone 7821 MPP	No	No	No	No	No
Cisco IP Phone 7841 MPP	No	No	No	No	No
Cisco IP Phone 7861 MPP	No	No	No	No	No
Cisco IP Conference Phone 7832	No	No	No	No	No
Cisco IP Conference Phone 7832 MPP	No	No	No	No	No

Model	Local Config	Remote Firmware Upgrade / Management	Inventory Management	Diagnostics	Remote Config
Cisco IP Phone 8811	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco Wireless IP Phone 8821	No	No	No	No	No
Cisco IP Phone 8841	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco IP Phone 8845	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco IP Phone 8851	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later

Model	Local Config	Remote Firmware Upgrade / Management	Inventory Management	Diagnostics	Remote Config
Cisco IP Phone 8861	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco IP Phone 8865	Yes Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco IP Phone 8865NR	Yes: Phone load 12.5(1)SR2 or later Headset load 1.0(2) or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Phone load 12.5(1)SR3 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco IP Phone 8811 MPP	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No
Cisco IP Phone 8841 MPP	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No

Model	Local Config	Remote Firmware Upgrade / Management	Inventory Management	Diagnostics	Remote Config
Cisco IP Phone 8845 MPP	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No
Cisco IP Phone 8851 MPP	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No
Cisco IP Phone 8861 MPP	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No
Cisco IP Phone 8865 MPP	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No	Yes: Phone load 11.2(3) or later Headset load 1.0(2) or later	No
Cisco IP Conference Phone 8832/8832NR	No	No	No	No	No
Cisco IP Conference Phone 8832 MPP	No	No	No	No	No
Cisco IP Phone 6900/79x2/79x5/8900/9900 Series	No	No	No	No	No
Cisco SPA Series IP Phone	No	No	No	No	No
Cisco Jabber Client - Desktop	Yes: Jabber load 12.6MR or later Headset load 1.5(1) or later	Yes: Jabber load 12.6MR or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Jabber load 12.6MR or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Jabber load 12.7 or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Jabber load 12.6MR or later Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco Jabber Client - Mobile	No	No	No	No	No

Model	Local Config	Remote Firmware Upgrade / Management	Inventory Management	Diagnostics	Remote Config
Cisco Jabber Client - VDI	Yes: Jabber load 12.6MR or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later	Yes: Jabber load 12.6MR or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Jabber load 12.6MR or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Jabber load 12.7 or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later	Yes: Jabber load 12.6MR or later for Win32 Jabber Load 12.7MR or later for Win64 Headset load 1.5(1) or later CUCM 12.5(1)SU1/ 11.5(1)SU7 or later
Cisco Webex Teams - Desktop	No	No	No	No	No
Cisco Webex Desktop Series	No	No	No	No	No
Cisco Webex Meetings	No	No	No	No	No
Cisco UC-One	No	No	No	No	No
Microsoft Skype for Business	No	No	No	No	No

Product specifications

Table 8. Product specifications for the Cisco Headset 500 Series

Headset detail	
Connectivity options	PC, Mac, Cisco IP phone, DX endpoint (see Platform Support above)
Hearing protection	Yes (requires USB headset adapter or wireless base) Acoustic spike protection from sounds to over 118 dB
Microphone type	Electret condenser/ECM
Microphone directionality	Unidirectional
Microphone frequency response	150 to 6800 Hz
Speaker impedance	~90 ohms

Headset detail	
Earpiece bandwidth	50 Hz to 18 kHz
Maximum sound pressure	118 db SPL(A) (requires USB adapter or wireless base)
In-call presence indicator on ear plate	LED on each ear plate (requires USB headset adapter or wireless base)

Table 9. Product specifications for Cisco Headset 561 and 562 Standard Base Station

Headset detail	
Wireless technology	DECT 6.0 (or region-specific)
Range	Up to 100 meters (333 feet)
Battery life	Storage: up to 200 days Standby: up to 60 hours Active use: up to 10 hours
Connectivity	1 simultaneous connection (USB or RJ9/RJ11 Y) All cables included
Audio bandwidth	Narrowband (8 kHz) Wideband (16 kHz) Full band (48 kHz)

Ordering information

The Cisco Headset 500 Series is available now. To order, visit [the Cisco Ordering Home Page](#).

Table 10. Ordering information for Cisco Headset 521, 522, 531, and 532

Part number	Product description
CP-HS-W-521-USB=	Cisco Headset 521 (Wired Single with 3.5mm connector and USB-A Adapter)
CP-HS-W-522-USB=	Cisco Headset 522 (Wired Dual with 3.5mm connector and USB-A Adapter)
CP-HS-W-521-USBC	Cisco Headset 521 (Wired Single with 3.5mm connector and USB-C Adapter)
CP-HS-W-522-USBC	Cisco Headset 522 (Wired Dual with 3.5mm connector and USB-C Adapter)
CP-HS-W-531-RJ=	Cisco Headset 531 (Wired Single with Quick Disconnect coiled RJ Headset Cable)
CP-HS-W-532-RJ=	Cisco Headset 532 (Wired Dual with Quick Disconnect coiled RJ Headset Cable)
CP-HS-W-531-USBA=	Cisco Headset 531 (Wired Single with USB-A Headset Adapter)
CP-HS-W-532-USBA=	Cisco Headset 532 (Wired Dual with USB-A Headset Adapter)
CP-HS-W-531-USBC	Cisco Headset 531 (Wired Single with USB-C Headset Adapter)

Part number	Product description
CP-HS-W-532-USBC	Cisco Headset 532 (Wired Dual with USB-C Headset Adapter)
CP-HS-W-USBA=	Cisco USB-A Headset Adapter (optional accessory) for 530 Series
CP-HS-W-RJ=	Cisco QD RJ Headset Cable (optional accessory) for 530 Series
CP-HS-W-5EC8=	Cisco 8-pack Ear Pad Spare (optional accessory) for 520 and 530 Series
CP-HS-W-USBC	Cisco QD USB-C Headset Adapter (optional accessory) for 530 Series
CP-HS-W-YQD=	Cisco QD Y Trainer Cable (optional accessory) for 530 Series

Table 11. Ordering information for Cisco Headset 561 and 562 with Standard Base Station

Part number	Product description
CP-HS-WL-561-S-US=	Cisco Headset 561 Wireless Single Headset with Standard Base Station. Frequency Band: United States-Canada
CP-HS-WL-562-S-US=	Cisco Headset 562 Wireless Dual Headset with Standard Base Station. Frequency Band: United States-Canada
CP-HS-WL-561-S-EU=	Cisco Headset 561 Wireless Single Headset with Standard Base Station. Frequency Band: Europe, U.K., Asia, South Africa, Hong Kong, Australia, New Zealand
CP-HS-WL-562-S-EU=	Cisco Headset 562 Wireless Dual Headset with Standard Base Station. Frequency Band: Europe, U.K., Asia, South Africa, Hong Kong, Australia, New Zealand
CP-HS-WL-561-S-LA=	Cisco Headset 561 Wireless Single Headset with Standard Base Station. Frequency Band: Latin America
CP-HS-WL-562-S-LA=	Cisco Headset 562 Wireless Dual Headset with Standard Base Station. Frequency Band: Latin America

Table 12. Ordering information for Cisco Headset 561 and 562 with Multibase Station

Part number	Product description
CP-HS-WL-561-M-US=	Cisco Headset 561 Wireless Single Headset with Multibase Station. Frequency Band: United States-Canada
CP-HS-WL-562-M-US=	Cisco Headset 562 Wireless Dual Headset with Multibase Station. Frequency Band: United States-Canada
CP-HS-WL-561-M-EU=	Cisco Headset 561 Wireless Single Headset with Multibase Station. Frequency Band: Europe, U.K., Asia, South Africa, Hong Kong, Australia, New Zealand
CP-HS-WL-562-M-EU=	Cisco Headset 562 Wireless Dual Headset with Multibase Station. Frequency Band: Europe, U.K., Asia, South Africa, Hong Kong, Australia, New Zealand
CP-HS-WL-561-M-LA=	Cisco Headset 561 Wireless Single Headset with Multibase Station. Frequency Band: Latin America
CP-HS-WL-562-M-LA=	Cisco Headset 562 Wireless Dual Headset with Multibase Station. Frequency Band: Latin America

Table 13. Ordering information for Cisco Headset 561 and 562 optional accessories

Product Number	Description
CP-HS-WL-561-N-US=	Cisco Headset 561 Spare Wireless Single Headset Only with No Base Station. Requires Base Station. Frequency Band: United States-Canada
CP-HS-WL-562-N-US=	Cisco Headset 562 Spare Wireless Dual Headset Only with No Base Station. Requires Base Station Frequency Band: United States-Canada
CP-HS-WL-561-N-EU=	Cisco Headset 561 Spare Wireless Single Headset Only with No Base Station. Requires Base Station. Frequency Band: Europe, U.K., Asia, South Africa, Hong Kong, Australia, New Zealand
CP-HS-WL-562-N-EU=	Cisco Headset 562 Spare Wireless Dual Headset Only with No Base Station. Requires Base Station Frequency Band: Europe, U.K., Asia, South Africa, Hong Kong, Australia, New Zealand
CP-HS-WL-561-N-LA=	Cisco Headset 561 Spare Wireless Single Headset Only with No Base Station. Requires Base Station. Frequency Band: Latin America
CP-HS-WL-562-N-LA=	Cisco Headset 562 Spare Wireless Dual Headset Only with No Base Station. Requires Base Station Frequency Band: Latin America
CP-HS-WL-5EC8=	Cisco 8-pack Ear Pad Spare (optional accessory) for 560 Series
CP-HS-WL-USBA-C	Cisco USB-A to USB-C Spare Cable (optional accessory) for 560 Series
CP-HS-WL-MUSB-C	Cisco Micro-USB to USB-C Spare Cable (optional accessory) for 560 Series
CP-HS-WL-5ACA=	Cisco AC Power Adapter Spare (optional accessory) for 560 Series

Warranty information

The Cisco Headset 521, 522, 531, and 532 models have a two-year limited liability warranty.

The Cisco Headset 561 and 562 models have a one-year limited liability warranty.

Cisco environmental sustainability

Information about Cisco’s environmental sustainability policies and initiatives for our products, solutions, operations, and extended operations or supply chain is provided in the “Environment Sustainability” section of Cisco’s [Corporate Social Responsibility](#) (CSR) Report.

Reference links to information about key environmental sustainability topics (mentioned in the “Environment Sustainability” section of the CSR Report) are provided in the following table:

Sustainability topic	Reference
Information on product material content laws and regulations	Materials
Information on electronic waste laws and regulations, including products, batteries, and packaging	WEEE compliance

Cisco makes the packaging data available for informational purposes only. It may not reflect the most current legal developments, and Cisco does not represent, warrant, or guarantee that it is complete, accurate, or up to date. This information is subject to change without notice.

Cisco Capital

Flexible payment solutions to help you achieve your objectives

Cisco Capital makes it easier to get the right technology to achieve your objectives, enable business transformation and help you stay competitive. We can help you reduce the total cost of ownership, conserve capital, and accelerate growth. In more than 100 countries, our flexible payment solutions can help you acquire hardware, software, services and complementary third-party equipment in easy, predictable payments. [Learn more.](#)

For more information

Amplify the headset experience with the Cisco Headset 500 Series. Enjoy a reliable experience with Cisco IP phones and soft clients.

For additional information, visit <https://www.cisco.com/go/headsets>.

Americas Headquarters
Cisco Systems, Inc.
San Jose, CA

Asia Pacific Headquarters
Cisco Systems (USA) Pte. Ltd.
Singapore

Europe Headquarters
Cisco Systems International BV Amsterdam,
The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at <https://www.cisco.com/go/offices>.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)